SPLIT-TYPE AIR CONDITIONER



WI-FI FUNCTION USER MANUAL



This description is applied to Air Conditioners with Wi-Fi function. Please read the manual carefully before using the product and keep it for future reference.

WI-FI MODULE SPECIFICATION AND OPERATION GUIDELINE

- 1. Minimum specifications on a smartphone: Android 5.0 version or higher IOS 9.0 version or higher
- 2. Basic parameters for Wi-Fi module

Parameters	Details
Network frequency	2.400 - 2.4835 GHz
Standards of WLAN	IEEE 802.11 b/g/n (channels 1-14,channels 1-13 for EU/AU,channels 1-11 for US/CA)
Protocol stack support	IPv4/TCP/UDP/HTTPS/TLS/DNS
Security support	WEP/WPA/WPA2/AES128
Network type support	STA/AP/STA+AP
Max. RF Power	18.5 dbm
Blue tooth frequency	2.402 - 2.480 GHz
Blue tooth RF Power	9 dbm

3. Operation guideline. Please use the simple guideline instructions below as reference.

Operation Steps	Operation Items	New Account	Re-install APP (registered before)
Step 1	Download and Install APP	YES	YES
Step 2	Activate APP	YES	YES
Step 3	Account Registration	YES	NO
Step 4	Login	YES	YES
Step 5	Add Device to control	YES	Registered Device will remain

Note: If you registered the account and added device before, when you re-install the APP again and login, the added device will remain.

DOWNLOAD AND INSTALL THE APP





iOS



Tesla Smart

For Android smartphones

Method 1: Please scan the QR code with a browser scanner, download and install the APP.Method 2: Open the Google "Play Store" on your smartphone and search "Tesla Smart", download and install the APP.

For IOS smartphones

Method 1: Please scan the QR code and follow the tips to get into "AppStore", download and install the APP.

Method 2: Open the Apple "AppStore" on your smartphone and search "Tesla Smart Things", download and install the APP.

Note: Please enable the Storage/Location/Camera permissions for this APP during the installation. Otherwise it will have some problems when operating.

REGISTRATION

- 1. If you don't have an account please tap the "Register" button.
- 2. Read the Privacy Policy and tap "Agree".



login

- 1. Tap "Sign in with an existing account".
- 2. Enter your registered account username and password.
- 3. Tap the "Sign in" button.



Country Ch	oosed
Search	
A	
Afghanistan	
Albania	
Algeria	
Angola	
Argentina	
Armenia	
Australia	Y Z

REGISTRATION

- 1. Enter the verification code you received via e-mail.
- 2. Set the Password with 6-20 characters, including characters and numbers.
- 3. Tap "Done".



LOGIN

- 1. Tap "Log in with existing account".
- 2. Enter your registered account username and password.
- 3. Tap "Log in" button.



Forgot the password

If you forgot the password or you want to reset the password, follow these steps:

- 1. Tap "Forgot password".
- 2. Enter your account username (e-mail address) and tap the "Obtain verification code" button.

<

Entor vorification

- 3. Enter the verification code received via e-mail.
- 4. Set the new password and tap the "Done" button.

		code
Login	Forgot password	* * * * * *
****** >	***** >	Verification code is sent to your email:
Email address	***** X	**************************************
Password		
	Obtain verification code	↓ ←
Log in	Obtain verification code	Set Password
Log in Forgot password	Obtain verification code	← Set Password ***** ∞
Log in Forget password	Obtain verification code	Set Password ***** 6-20 characters for password, including character, numbers
Log in Forgot password	Obtain verification code	Set Password ***** 6-20 characters for password, including character, numbers

AP MODE

- 1. Power on the indoor unit
- 2. Click "+" in the upper right corner of the Home screen
- 3. Select "Large Home Appliances"
- 4. Tap the "Air conditioner (Wi-Fi)" logo
- 5. Connect to the Wi Fi network
- 6. Follow the comments on the screen to reset the Wi-Fi module

- For F series modem is reset by pressing the "HEALTH" button 8 times on the remote, within 10 seconds

- For Q series modem is reset by pressing "[Cooling] and [+] simultaneously for 3 seconds An audible signal will announce that the modem has been successfully reset Check "Confirm the device is reset" and tap "Next"

- 7. In the upper right corner change the connection method to "AP mode" and tap "Next"
- 8. Input the password of the Wi-Fi to which your smartphone is connected, then tap "Next"
- 9. Follow the instructions and connect to AC's hotspot "SmartLifeXXXX"
- 10. You can see the percentage rate of the connection process, in real time.

<	Add Manually Auto S	can 🖂	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical	Air Conditioning		Select 2.4 GHz Wi-Fi	Reset the device first.	Reset the de
Lighting	Air Air Conditioner Conditioner	Air Conditioner	Network and enter password. If your Wi-Fi is 5GHz, please set it to be 2.4GHz. Common router setting method	Power on the device and confirm that the indicator is blinking rapidly. Note: please complete the network	Please power on AP Mode the indicator is bit AP Mode Note: please complete the network
Sensors	(802+W+1) (W+1)			distribution within 3 minutes after resetting the device.	distribution within 3 minutes after resetting the device.
Small Home Ap	Air Portable Air Conditioner (NB-IoT) (Wi-Fi)	Air Conditioner (Wi-Fi)	x 10.41 - 804a ✓ 10.41 - 2.40ha = + 7 ⊙		
Kitchen Appliances	Refrigerator				
Exercise & Health	Refrigerator (BLE+Wi-Fi) (Wi-Fi)	Refrigerator (BLE)	≈ ≒	Perform net pairing as prompted. >	Perform net pairing as prompted.
Security & Video Sur	Water Heater		۵ 🔹		
Control	Water Heater (BLE+Wi-Fi) (Wi-Fi)	Gas Water Heater	Next	- Confirm the indicator is blinking	Confirm the indicator is bigling
Entertainm	2 7			rapidly.	slowly.
Industry & Agriculture	Gas Water Solar water Heater beater (Wi-Fi) (BLE+Wi-Fi)	Solar water heater (Wi-Fi)			
Cancel			Cancel	Cancel	Done
Conne the de	ect your mobile phone	to	Adding device	Adding device	Added successfully
1. Please shown b	e connect your phone to the hol elow	spat	Ensure that the device is powered on.	Ensure that the Wi-Fi signal is good.	Tesla AC 2
× s	marilile-XXXX	* (1)			
4	P. Topo duese P. Topo lateonet				
2. Return devices	n to this app and continue ad	ding	Q		
			01:57	01:36	
			@ ©	00	

ENG

AIR CONDITIONER CONTROL

The device control screen will pop up automatically after adding the device. The device control screen will pop up manually by tapping the device name on the Home screen.

		٨		0		
		— Tesla	AC			
		Tesl	a Air6			
		Tesla	a Air3			
		Â	¢.	Q.		
÷		∠		÷		
	Room temp: 250				10000 1000 2000 26 °	
Said	Low DOSwing	Schedule		i 🔆 Hist	Auto UD Seing	Schedule
	- Temp				Temp —	
Sing	OFF	\$ uector		Skep	OFF	Careton

СПЕЦИФИКАЦИЯ НА WI-FI МОДУЛА И РЪКОВОДСТВО ЗА РАБОТА

- 1. Минимални спецификации на смартфона: Версия на Android 5.0 или по-висока Версия на IOS 9.0 или по-висока
- 2. Основни параметри на Wi-Fi модула

Параметри	Данни
Честота на мрежата	2.400 - 2.4835 GHz
Стандарти на WLAN	IEEE 802.11 b/g/n (канали 1-14, канали 1-13 за ЕС/АФРИКАНСКИ СЪЮЗ, канали 1-11 за САЩ/КАНАДА)
Поддръжка на протоколи	IPv4/TCP/UDP/HTTPS/TLS/DNS
Поддръжка на защита	WEP/WPA/WPA2/AES128
Поддръжка на тип мрежа	STA/AP/STA+AP
Макс. радиочестотна мощност	18.5 dbm
Чества на Bluetooth	2.402 - 2.480 GHz
Радиочестотна мощност на Bluetooth	9 dbm

3. Ръководство за работа. Моля, използвайте простите указания по-долу за справка.

Стъпки на работа	Действия	Нов акаунт	Преинсталиране на приложението (регистрирано преди това)
Стъпка 1	Изтегляне и инсталиране на приложението	ДА	ДА
Стъпка 2	Активиране на приложението	ДА	ДА
Стъпка 3	Регистрация на акаунт	ДА	HE
Стъпка 4	Влизане	ДА	ДА
Стъпка 5	Добавяне на устройство за управление	ДА	Регистрираното устройство остава

Забележка: Ако сте регистрирали акаунта и сте добавили устройство преди това, когато отново инсталирате приложението и влезете в него, добавеното устройство ще остане.

ИЗТЕГЛЯНЕ И ИНСТАЛИРАНЕ НА ПРИЛОЖЕНИЕТО









Tesla Smart

За смартфони с Android

- Метод 1: Моля, сканирайте QR кода със скенер на браузъра, изтеглете и инсталирайте приложението.
- **Метод 2:** Отворете Google "Play Store" на смартфона си и потърсете "Tesla Smart", изтеглете и инсталирайте приложението.

За смартфони с IOS

- **Метод 1:** Моля, сканирайте QR кода и следвайте съветите, за да влезете в "AppStore", изтеглете и инсталирайте приложението.
- Merog 2: Отворете AppStore на Apple на вашия смартфон и потърсете "Tesla Smart Things", изтеглете и инсталирайте приложението.

Забележка: Моля, активирайте разрешенията за съхранение/местоположение/камера за това приложение по време на инсталацията. В противен случай то ще има проблеми при работата си.

РЕГИСТРАЦИЯ

- 1. Ако нямате акаунт, натиснете бутона "Register" (Регистрация).
- 2. Прочетете Политиката за поверителност и докоснете "Agree" (Съгласен съм).



влизане

- 1. Докоснете "Sign in with an existing account" (Влизане със съществуващ акаунт).
- 2. Въведете потребителското име и паролата на регистрирания си акаунт.
- 3. Докоснете бутона "Sign in" (Влизане).

*****		x
Obtain verification	code	
I Agree User agreement and P	rivacy Policy	

Country Ch	oosed
Search	
А	
Afghanistan	
Albania	
Algeria	
Angola	
Argentina	
Armenia	
Australia	¥ Z

РЕГИСТРАЦИЯ

- 1. Въведете кода за потвърждение, който сте получили по имейл.
- 2. Задайте парола с 6-20 символа, включително знаци и цифри.
- 3. Докоснете "Done" (Готово).



ВЛИЗАНЕ

- 1. Докоснете "Log in with existing account" (Влизане със съществуващ акаунт).
- 2. Въведете потребителското име и паролата на регистрирания си акаунт.
- 3. Докоснете бутона "Log in" (Влизане).



Забравена парола

Ако сте забравили паролата или искате да я възстановите, следвайте следните стъпки:

- 1. Докоснете "Forgot password" (Забравена парола).
- 2. Въведете потребителското име на акаунта си (имейл адрес) и докоснете бутона "Obtain verification code" (Получаване на код за проверка).

Х

- 3. Въведете кода за проверка, получен по имейл.
- 4. Задайте новата парола и докоснете бутона "Done" (Готово).

		Forgot pa	ssword
>		*****	>

		Obtain veri	fication code
word			
<u>ment</u> and			
	> word	> word	> Forgot pas



РЕЖИМ НА ТОЧКА ЗА ДОСТЪП (АР)

- 1. Включете вътрешното тяло
- 2. Щракнете върху "+" в горния десен ъгъл на началния екран
- 3. Изберете "Large Home Appliances" (Големи домакински уреди).
- 4. Докоснете логото "Air conditioner (Wi-Fi)"
- 5. Свържете се с Wi Fi мрежата
- 6. Следвайте коментарите на екрана, за да нулирате Wi-Fi модула - За серия F модемът се нулира чрез натискане 8 пъти на бутона "HEALTH" на дистанционното управление, в рамките на 10 секунди - За серията Q модемът се нулира чрез едновременно натискане на [Cooling] и [+] в продължение на 3 секунди

Звуков сигнал ще съобщи, че модемът е успешно нулиран. Сложете отметка на "Confirm the device is reset" (Устройството е нулирано) и докоснете "Next" (Напред)

- 7. В горния десен ъгъл променете метода на свързване "AP mode" (Точка на достъп) и докоснете "Next" (Напред)
- 8. Въведете паролата на Wi-Fi мрежата, към която е свързан смартфонът ви, след което докоснете "Next" (Напред)
- 9. Следвайте указанията и се свържете с точката за достъп на климатика "SmartLifeXXXX"
- 10. Можете да видите процентното съотношение на процеса на свързване в реално време.

<	Add Manually Auto S	Scan 🖯	Cancel	Cancel EZ Mode ==	Cancel AP Mode =
Electrical	Air Conditionir	9	Salact 2.4 GHz Wi-Ei	Depart the device first	EZ Mode Default
Lighting		_	Network and enter password.	Power on the device and confirm that the	Please power on
Sensors	Air Air Conditioner Conditioner (BLE+Wi-Fi) (Wi-Fi)	Air Conditioner (Zigbee)	If your Wi-Fi is 5GHz, please set it to be 2.4GHz. Common router setting method	indicator is blinking rapidly. Note: please complete the network distribution within 3 minutes after resetting the device.	the indicator is bit AP Mode Note: please complete the network distribution within 3 minutes after resetting the choice
Large Home Ap.,	Air Portable Air	Air	X VIA: BON		
Small Home Ap	(NB-IoT) (Wi-Fi)	(Wi-Fi)	→ 100 Fi+ 2.40hz 4 + 0	(• • •)	(
Kitchen Appliances	Refrigerator				
Exercise & Health	Refrigerator (BLE+Wi-Fi) (Wi-Fi)	Refrigerator (BLE)	? 4	Perform net pairing as prompted. \flat	Perform net pairing as prompted
Security & Video Sur	Water Heater				
Gateway Control		Ż	₿		
Energy	Water Heater Water Heater (BLE+Wi-Fi) (Wi-Fi)	Gas Water Heater (BLE+Wi-Fi)	Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking slowly.
Entertainm ent	Gas Water Solar water	Solar water			
And others in	(MLE) (DI E4WLE)	100000			
Agriculture	(min) (accounty	(W+Fi)			
Agriculture	(min) (account)	(W++)			
Agriculture	(mu) (arcun)	(W++)	Cancel	Cancel	Done
Cancel	ct your mobile phon	e to	Cancel	Cancel	Done
Cancel	ct your mobile phon	(Wirt)	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Four the WFI simal is post	Done Added successfully
Cancel Connee the de 1. Please shown br	ct your mobile phon vice's hotspot connect your phone to the he dow	e to	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Testa AC Device added successfully
Cancel Conne the de 1. Please shown br	ct your mobile phon vice's hotspot connect your phone to the he dow	e to Aspot	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Concentration Concen
Cancel Connet the de 1. Please shown br	ct your mobile phon vice's hotspot connect your phone to the he within within the hot state of the he within the hot state of the help markUle X000X	e to Aspat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Tesla AC Device added successfully
Cancel Conne the de 1. Please shown br	ct your mobile phon vice's hotspot connect your phone to the he fore WEAM martUle XXXX "Reg Buses "Reg Buses	e to Aspat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the WHFI signal is good.	Added successfully
Cancel Connee 1. Please shown br	ct your mobile phon vice's hotspot wice's hotspot with the second second second with the second second second markLife XXXX "Saa finance" to this app and continue a	(m+) e to stspot ¢ ()	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Added successfully
Cancel Connee 1. Please shown br	Cityour mobile phono vice's hotspot commet your phone to the he with the second second second second second second second second second second second second second second second second	(m+) e to kspot	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the WF# signal is good.	Added successfully Tests AC Device added successfully
Cancel Connee Connee Connee Connee Connee Shown Heave Shown Heave	City our mobile phon vice's hotspot wice's hotspot	(m+r)	Cancel Adding device Ensure that the device is powered on	Cancel Adding device Ensure that the WFFI signal is good.	Done Added successfully

УПРАВЛЕНИЕ НА КЛИМАТИКА

След добавяне на устройството ще се появи автоматично екранът за управление на устройството. Екранът за управление на устройството ще се появи ръчно, като докоснете името на устройството в Начален екран.



ΠΡΟΔΙΑΓΡΑΦΕΣ ΜΟΝΑΔΑΣ WI-FI ΚΑΙ ΓΕΝΙΚΕΣ ΟΔΗΓΙΕΣ ΛΕΙΤΟΥΡΓΙΑΣ

- Ελάχιστες προδιαγραφές smartphone: Έκδοση Android 5.0 ή μεταγενέστερη Έκδοση IOS 9.0 ή μεταγενέστερη
- 2. Βασικές παράμετροι μονάδας Wi-Fi

Παράμετροι	Λεπτομέρειες
Συχνότητα δικτύου	2.400 - 2.4835 GHz
Πρότυπα WLAN	IEEE 802.11 b/g/n (κανάλια 1-14, κανάλια 1-13 για ΕΕ/Αυστραλία, κανάλια 1-11 για ΗΠΑ/Καναδά)
Υποστηριζόμενα πρωτόκολλα	IPv4/TCP/UDP/HTTPS/TLS/DNS
Υποστηριζόμενα πρωτόκολλα ασφαλείας	WEP/WPA/WPA2/AES128
Υποστηριζόμενοι τύποι δικτύου	STA/AP/STA+AP
Μέγ. ισχύς ραδιοσυχνοτήτων	18.5 dbm
Συχνότητα Bluetooth	2.402 - 2.480 GHz
Ισχύς ραδιοσυχνοτήτων Bluetooth	9 dbm

 Γενικές οδηγίες λειτουργίας. Χρησιμοποιήστε τις παρακάτω απλές γενικές οδηγίες ως αναφορά.

Βήματα χειρισμού	Ενέργειες χειρισμού	Νέος λογαριασμός	Επανεγκατάσταση εφαρμογής (όπου έχει ήδη γίνει εγγραφή)
Βήμα 1	Λήψη και εγκατάσταση εφαρμογής	YES	YES
Βήμα 2	Ενεργοποίηση εφαρμογής	YES	YES
Βήμα 3	Καταχώριση λογαριασμού	YES	NO
Βήμα 4	Σύνδεση	YES	YES
Βήμα 5	Προσθήκη συσκευής στο χειριστήριο	YES	Registered Device will remain

Σημείωση: Αν έχει ήδη γίνει καταχώριση του λογαριασμού και προσθήκη της συσκευής, η συσκευή που έχετε προσθέσει παραμένει μετά από την επανεγκατάσταση της εφαρμογής και τη σύνδεση.

ΛΗΨΗ ΚΑΙ ΕΓΚΑΤΑΣΤΑΣΗ ΕΦΑΡΜΟΓΗΣ







iOS



Tesla Smart

Για smartphone με λειτουργικό Android

Μέθοδος 1: Σαρώστε τον κωδικό QR με το smartphone, χρησιμοποιώντας κατάλληλη εφαρμογή σάρωσης. Έπειτα, κάντε λήψη και εγκαταστήστε την εφαρμογή.

Μέθοδος 2: Ανοίξτε το «Play Store» της Google στο smartphone και αναζητήστε την εφαρμογή «Smart Life». Έπειτα, κάντε λήψη και εγκαταστήστε την εφαρμογή.

Για smartphone με λειτουργικό IOS

Μέθοδος 1: Σαρώστε τον κωδικό QR με το smartphone και ακολουθήστε τις οδηγίες για να ανοίξετε το «AppStore». Έπειτα, κάντε λήψη και εγκαταστήστε την εφαρμογή.

Μέθοδος 2: Ανοίξτε το «AppStore» της Apple στο smartphone και αναζητήστε την εφαρμογή «Tesla Smart Things». Έπειτα, κάντε λήψη και εγκαταστήστε την εφαρμογή.

Σημείωση: Ενεργοποιήστε τα δικαιώματα πρόσβασης της εφαρμογής στον Χώρο αποθήκευσης/ την Τοποθεσία/την Κάμερα κατά την εγκατάσταση. Διαφορετικά, θα υπάρξουν προβλήματα κατά τη λειτουργία της.

ΓΓΓΡΑΦΗ

- 1. Εάν δεν έχετε λογαριασμό, πατήστε το κουμπί «Register» (Εγγραφή).
- Διαβάστε την Πολιτική Απορρήτου και πατήστε «Agree» (Συμφωνώ).

Register Log in with Existing Account	We understandt privacy. Inorder our collection an information, we policy and user a accordance with regulations. Whe have fully read, u all of the update Agreement. Plea become familiar and if you have a free to contactus	te he importance of to morefully present d useof your personal haverevised our privacy greementin detail in the latest laws and en you click[Agree, you nderstood and accepted dPrivacy Policy and User se takesome time to with ourprivacy policy, ny questions, please feel t. d User Agreement
	Disagree	Agree

ΣΥΝΔΕΣΗ

- 1. Πατήστε «Sign in with an existing account» (Σύνδεση με υπάρχοντα λογαριασμό).
- 2. Εισαγάγετε το όνομα χρήστη και τον κωδικό πρόσβασης του λογαριασμού που έχετε καταχωρίσει.
- 3. Πατήστε το κουμπί «Sign in» (Σύνδεση).

	>
*****	х
Obtain verificat	ion code
I Agree User agreement	and Privacy Policy

Country Choosed	
Search	
A	
Afghanistan	
Albania	
Algeria	
Angola	
Argentina	
Armenia	
Australia	v Z

ΕΓΓΡΑΦΗ

- 1. Πληκτρολογήστε τον κωδικό επαλήθευσης που λάβατε μέσω e-mail.
- Ορίστε έναν κωδικό πρόσβασης με 6-20 χαρακτήρες, ο οποίος να περιλαμβάνει γράμματα και αριθμούς.
- 3. Πατήστε «Done» (Τέλος).



ΣΥΝΔΕΣΗ

- 1. Πατήστε «Log in with existing account» (Σύνδεση με υπάρχοντα λογαριασμό).
- 2. Εισαγάγετε το όνομα χρήστη και τον κωδικό πρόσβασης του λογαριασμού που έχετε καταχωρίσει.
- 3. Πατήστε το κουμπί «Log in» (Σύνδεση).



Ξεχάσατε τον κωδικό πρόσβασης;

Εάν ξεχάσατε τον κωδικό πρόσβασης ή θέλετε να τον επαναφέρετε, ακολουθήστε τα παρακάτω βήματα:

- Ϊ. Πατήστε «Forgot password» (Ξέχασα τον κωδικό πρόσβασής μου).
- Εισαγάγετε το όνομα χρήστη του λογαριασμού (διεύθυνση e-mail) και πατήστε το κουμπί «Obtain verification code» (Λήψη κωδικού επαλήθευσης).
- Πληκτρολογήστε τον κωδικό επαλήθευσης που λάβατε μέσω e-mail.
- Ορίστε νέο κωδικό πρόσβασης και πατήστε το κουμπί «Done» (Τέλος).

Login		Forgot pass	word
****	>	*****	>
Email address		******	x
Password		Obtain verifi	cation code
Log in		Obtain verni	cation code
Forgot pas	ssword		
Login means that you agree with User Agre	eement and		

<					
En	iter ve	erifi	cati	ion	
со	de				
*	* *	*	*	*	
Verificat ******	ion code is ****,Rese	sent t nd(55	o you ;)	r email:	
←					
Se	t Pass	wo	rd		
**	* * * *	<		•	
6-20 charac	ters for passwori	d, includin	g charact	er, numbers	
	Do	one)

ΛΕΙΤΟΥΡΓΙΑ ΑΡ

- 1. Ενεργοποιήστε την εσωτερική μονάδα.
- 2. Πατήστε το εικονίδιο «+» στην επάνω δεξιά γωνία της αρχικής οθόνης.
- 3. Επιλέξτε «Large Home Appliances» (Μεγάλες οικιακές συσκευές).
- 4. Πατήστε πάνω στο λογότυπο «Air conditioner (Wi-Fi)».
- 5. Συνδεθείτε στο δίκτυο Wi Fi
- 6. Ακολουθήστε τις οδηγίες που εμφανίζονται στην οθόνη για να επαναφέρετε τη μονάδα Wi-Fi - Για το μόντεμ της σειράς F η επαναφορά γίνεται πατώντας 8 φορές το κουμπί «HEALTH» του τηλεχειριστηρίου, εντός 10 δευτερολέπτων

- Για το μόντεμ της σειράς Q, η επαναφορά γίνεται με ταυτόχρονο πάτημα των πλήκτρων [Cooling] και [+] για 3 δευτερόλεπτα

Η επιτυχής επαναφορά του μόντεμ επιβεβαιώνεται με ένα ηχητικό σήμα Επιλέξτε «Confirm the device is reset» (Επιβεβαίωση επαναφοράς της συσκευής) και πατήστε «Next» (Επόμενο)

- Στην επάνω δεξιά γωνία, αλλάξτε τον τρόπο σύνδεσης σε «AP mode» (Λειτουργία AP) και πατήστε «Next» (Επόμενο)
- Εισαγάγετε τον κωδικό πρόσβασης του δικτύου Wi-Fi στο οποίο είναι συνδεδεμένο το smartphone σας και στη συνέχεια πατήστε «Next» (Επόμενο).
- 9. Ακολουθήστε τις οδηγίες και συνδεθείτε στο hotspot του κλιματιστικού «SmartLifeXXXX».
- 10. Μπορείτε να δείτε την πρόοδο της διαδικασίας σύνδεσης, με μορφή ποσοστού, σε πραγματικό χρόνο.

< .	Add Manually Auto Scan	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical Lighting Sensors	Air Conditioning	Select 2.4 GHz Wi-Fi Network and enter password. Hyour Wi-Fi is Sütz please set it to be 2.40Hz. Common router setting method	Reset the device first. Power on the device and confirm that the indicator is blinking rapidly. Note: please complete the network distribution within 3 minutes after resetting	Reset the de EZ Mode Betwin Please power on the middace is all Note: please compare are network derich classes all prefer the
Large Home Ap Small Home Ap Kitchen Appliances Exercise & Health	Ar Conditioner (NB-br)T Perturble Ar Conditioner Conditioner Conditioner Refrigerator Refrigerator Refrigerator Refrigerator		Perform net pairing as prompted. >	Perform ner pairing as prompted
Security & Video Sur Gateway Control Energy Entertainm ent	Water Heater	A ()	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking stowly.
Industry & Agriculture	(Wi-Fi) (BLE+Wi-Fi) (Wi-Fi)			
Industry & Agriculture	(Wi-Fi) (BLE+Wi-Fi) (Wi-Fi)	Cancel	Cancel	Done
Cancel	(no ra) (BLE+WA PA) (No ray) ct your mobile phone to vice's hotspot connect your phone to the hotspot know	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Tesia AC Device added successfully
Industry & Agriculture Cancel Conne the der 1, Pierate Show Sh Sh Sh Sh Sh Sh Sh Sh Sh Sh Sh Sh Sh	0x+9 BL2-0x+9 0x+9 ct your mobile phone to Vice's hotspot Contract your phone to be noticed to the notice of the noticed mark/lex.000 Contract your phone to be noticed to the noticed of the noticed mark/lex.000 mark/lex.000 Contract your phone to be noticed mark/lex.000 Contract your phone to be noticed mark/lex.000 mark/lex.000 Contract your phone to be noticed mark/lex.000 Contract your phone to be noticed mark/lex.000 to be not phone to be not ph	Cancel Adding device Ensure that the device is powered on	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Tesia AC Device added successfully

ΕΛΕΓΧΟΣ ΚΛΙΜΑΤΙΣΤΙΚΟΥ

Μετά από την προσθήκη της συσκευής, εμφανίζεται αυτόματα η οθόνη ελέγχου της συσκευής. Αν θέλετε να προβάλετε την οθόνη ελέγχου της συσκευής με μη αυτόματο τρόπο, πατήστε το όνομα της συσκευής στην αρχική οθόνη.

		۵		0		
		Tesla	AC			
		Tesh	a Air6			
		Tesla	a Air3			
		A	Ç.	ę•		
		_				
	Tesla AC Room temp: 25°C 26°C	2		¢	Tesla AC Room temp: 20% 26°	
a ^t la		0		*	Are the	
के कुलि (Sold	Low 0.0 Swing	Schedule		Hist	Auto UID Seing Sch	dule
	Temp —				Temp	
C Strep	OFF	¢)		Steep	OFF (used on the second	

SPECIFIKACIJA I SMJERNICE ZA RAD WI-FI MODULA

- 1. Minimalne specifikacije na pametnom telefonu: Android 5.0 verzija ili novija IOS 9.0 verzija ili novija
- 2. Osnovni parametri za Wi-Fi modul

Parametri	Pojedinosti
Frekvencija mreže	2.400 - 2.4835 GHz
Standardi WLAN-a	IEEE 802.11 b/g/n (kanali 1-14, kanali 1-13 za EU/AU, kanali 1-11 za SAD/Kanada)
Podrška protokola	IPv4/TCP/UDP/HTTPS/TLS/DNS
Sigurnosna podrška	WEP/WPA/WPA2/AES128
Podrška za vrstu mreže	STA/AP/STA+AP
Maks. RF snaga	18.5 dbm
Bluetooth Frekvencija	2.402 - 2.480 GHz
Bluetooth RF snaga	9 dbm

3. Smjernica za rad. Kao referencu koristite donje jednostavne smjernice.

Radni koraci	Stavke operacije	Novi profil	Ponovno instalirajte APP (registriran ranije)
Korak 1	Preuzmite i instalirajte APLIKACIJU	DA	DA
Korak 2	Aktivirajte APP	DA	DA
Korak 3	Registracija računa	DA	NE
Korak 4	Prijava	DA	DA
Korak 5	Dodajte uređaj za kontrolu	DA	Registrirani uređaj će ostati

Bilješka:Ako ste prije registrirali račun i dodali uređaj, kada ponovno instalirate APP i prijavite se, dodani uređaj će ostati.

PREUZMITE I INSTALIRAJTE APLIKACIJU





iOS



Tesla Smart

Za Android pametne telefone

Metoda 1: Skenirajte QR kod skenerom preglednika, preuzmite i instalirajte APP.
 Metoda 2: Otvorite Google "Play Store" na svom pametnom telefonu i potražite "Tesla Smart", preuzmite i instalirajte APP.

Za IOS pametne telefone

Metoda 1: Skenirajte QR kod i slijedite savjete kako biste ušli u "AppStore", preuzeli i instalirali APP.
 Metoda 2: Otvorite Apple "AppStore" na svom pametnom telefonu i potražite "Tesla Smart Things", preuzmite i instalirajte APP.

Bilješka: Omogućite dopuštenja za pohranu/lokaciju/kameru za ovu APLIKACIJU tijekom instalacije. Inače će aplikacija imati problema tijekom rada.

REGISTRACIJA

- 1. Ako nemate račun, dodirnite gumb "Registracija".
- 2. Pročitajte Politiku privatnosti i dodirnite "Slažem se".



PRIJAVA

- 1. Dodirnite "Prijava s postojećim računom".
- 2. Unesite korisničko ime i lozinku vašeg registriranog računa.
- 3. Dodirnite gumb "Prijava".

Resister	
	>
*****	Х
Obtain verifica	ation code
•	
I Agree User agreeme	nt and Privacy Policy

Country Choosed		
Search		
A		
Afghanistan		
Albania		
Algeria		
Angola		
Argentina		
Armenia		
Australia	Y Z	

 \odot

REGISTRACIJA

- 1. Unesite kontrolni kod koji ste primili putem e-maila.
- 2. Postavite lozinku sa 6-20 znakova, uključujući znakove i brojeve.
- 3. Dodirnite "Gotovo".



PRIJAVA

- 1. Dodirnite "Prijava s postojećim računom".
- 2. Unesite korisničko ime i lozinku vašeg registriranog računa.
- 3. Dodirnite gumb "Prijava".



Zaboravili ste lozinku

Ako ste zaboravili lozinku ili je želite poništiti, slijedite ove korake:

- 1. Dodirnite "Zaboravljena lozinka".
- 2. Unesite korisničko ime svog računa (adresu e-pošte) i dodirnite gumb "Dobijte kod za provjeru".

<

- 3. Unesite kod za provjeru primljen putem e-maila.
- 4. Postavite novu lozinku i dodirnite gumb "Gotovo".

		code
Login	Forgot password	* * * * * *
****** >	***** >	Verification code is cont to your emails
Email address	******** X	******************,Resend(55s)
Password		÷
Log in	Obtain verification code	Set Password
Forgot password		***** 0
		6 20 characters for password, including character, numbers
Login means that you agree with <u>User Agreement</u> and <u>Privacy Policy</u>		Done

AP NAČIN RADA

- 1. Uključite unutarnju jedinicu
- 2. Pritisnite "+" u gornjem desnom kutu početnog zaslona
- 3. Odaberite "Veliki kućanski aparati"
- 4. Dodirnite logotip "Klima uređaj (Wi-Fi)"
- 5. Spojite se na Wi-Fi mrežu
- 6. Slijedite komentare na zaslonu za resetiranje Wi-Fi modula

- Za seriju F modem se resetira pritiskom na tipku "HEALTH" 8 puta na daljinskom upravljaču, unutar 10 sekundi

 - Za Q seriju modem se resetira pritiskom na "[Hlađenje] i [+] istovremeno u trajanju od 3 sekunde Zvučni signal će javiti da je modem uspješno resetiran. Provjerite "Potvrdi da je uređaj resetiran" i dodirnite "Dalje"

- 7. U gornjem desnom kutu promijenite način povezivanja na "AP način" i dodirnite "Dalje"
- 8. Zatim unesite lozinku za Wi-Fi na koji je vaš pametni telefon povezan i dodirnite "Dalje"
- 9. Slijedite upute i spojite se na AC hotspot "SmartLifeXXXX"
- 10. Možete vidjeti postotak procesa povezivanja, u stvarnom vremenu.

<	Add Manually Auto Scan 🕀	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical Lighting	Air Conditioning	Select 2.4 GHz Wi-Fi Network and enter password.	Reset the device first. Power on the device and confirm that the indicator is blinking rapidly.	Reset the de Please power on the indicator is bi
Sensors Large Home Ap	Conditioner Conditioner (BLE+W-FI) (W-FI) (Zigbee)	2.4GHz. Common router setting method	Note: please complete the network distribution within 3 minutes after resetting the device.	Note: please complete the network distribution within 3 minutes after resetting the device.
Small Home Ap	Air Portable Air Air Conditioner Conditioner Conditioner (NB-toT) (Wi-Fi) (Wi-Fi) Refrigerator	x (117) 1.000 10 → 1959 - 2.400 1 + 7 ○		
Appliances Exercise & Health	Refrigerator Refrigerator	@ ==	Perform net pairing as prompted. >	Perform net pairing as prompted
Security & Video Sur Gateway	Water Heater	۵ ۵		
Control Energy	Water Heater Water Heater Gas Water (BLE+Wi-Fi) (Wi-Fi) Heater (BLE+Wi-Fi)	Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking slowly.
Entertainm ent Industry & Agriculture	Gas Water Heater (Wi-Fi) (BLE+Wi-Fi) (Wi-Fi)			
Cancel		Cancel	Canaal	Dogo
Conne the de	ect your mobile phone to vice's hotspot	Adding device	Adding device	Added successfully
1. Please shown be	connect your phone to the hotspot elow	Ensure that the device is powered on.	Ensure that the Wi-Fi signal is good.	Tesla AC 2 Device added successfully
~ Si	mariLife XXXX 🔹 🐨 🕕			
 Return devices 	 Tops litrane to this app and continue adding 			
		01:57	01:36	
		C Scan Register on Initialize the devices. Cloud. device.	Scan Register on Initialize the devices. Cloud, device.	

UPRAVLJANJE KLIMA UREĐAJEM

Kontrolni zaslon uređaja automatski će se pojaviti nakon dodavanja uređaja. Zaslon za upravljanje uređajem iskočit će ručno pritiskom na naziv uređaja na početnom zaslonu.



WI-FI MODUL SPECIFIKÁCIÓ ÉS MŰKÖDÉSI ÚTMUTATÓ

- Minimális okostelefon specifikációk: Android 5.0 vagy újabb verzió iOS 9.0 vagy újabb verzió
- 2. Wi-Fi modul alapvető paraméterei:

Paraméterek	Részletek
Hálózati frekvencia	2.400 - 2.4835 GHz
WLAN szabványok	IEEE 802.11 b/g/n (1-14 csatorna, EU/AU esetén 1-13 csatorna, US/CA esetén 1-11 csatorna)
Protokoll támogatás	IPv4/TCP/UDP/HTTPS/TLS/DNS
Biztonsági támogatás	WEP/WPA/WPA2/AES128
Hálózati típus támogatás	STA/AP/STA+AP
Maximális RF teljesítmény	18.5 dbm
Bluetooth frekvencia	2.402 - 2.480 GHz
Bluetooth RF teljesítmény	9 dbm

3. Működési útmutató: Kérjük, használja az alábbi egyszerű útmutatót referenciaként.

Lépések	Műveletek	Új fiók	Alkalmazás újratelepítése
1. lépés	Alkalmazás letöltése és telepítése	lgen	lgen
2. lépés	Alkalmazás aktiválása	lgen	lgen
3. lépés	Fiók regisztrációja	lgen	Nem
4. lépés	Bejelentkezés	lgen	lgen
5. lépés	Eszköz hozzáadása a vezérléshez	lgen	A regisztrált eszköz megmarad

Megjegyzés: Ha korábban már regisztrálta a fiókot és hozzáadta az eszközt, az alkalmazás újratelepítése és bejelentkezés után az eszköz megmarad.

ALKALMAZÁS LETÖLTÉSE ÉS TELEPÍTÉSE







Tesla Smart

Android

módszer: olvassa be a QR-kódot egy böngésző szkennerrel, töltse le és telepítse az alkalmazást.
 módszer: nyissa meg a Google "Play Áruházat" okostelefonján, és keresse meg a "Tesla Smart" alkalmazást, töltse le és telepítse az alkalmazást.

IOS

 módszer: olvassa be a QR-kódot, és kövesse az utasításokat az "AppStore"-ba való belépéshez, töltse le és telepítse az alkalmazást.

 módszer: Nyissa meg az Apple "AppStore"-t okostelefonján, és keresse meg a "Tesla Smart Things" alkalmazást, töltse le és telepítse az alkalmazást.

Megjegyzés: Kérjük, engedélyezze a tárhely/hely/kamera hozzáférést az alkalmazás telepítése során. Ellenkező esetben problémák léphetnek fel a működés során.

REGISZTRÁCIÓ

- 1. Ha még nincs fiókja, kérjük, kattintson a "Regisztráció" gombra.
- 2. Olvassa el az Adatvédelmi szabályzatot, és koppintson az "Elfogadom" gombra.



BEJELENTKEZÉS

- 1. Érintse meg a "Bejelentkezés meglévő fiókkal" gombot.
- 2. Adja meg a regisztrált fiók felhasználónevét és jelszavát.
- 3. Érintse meg a "Bejelentkezés" gombot.

x
х
ode
y Policy

Country Choosed		
Search		
A		
Afghanistan		
Albania		
Algeria		
Angola		
Argentina		
Armenia		
Australia	¥ Z	

REGISZTRÁCIÓ

- 1. Adja meg az e-mailben kapott ellenőrző kódot.
- 2. Állítson be egy 6-20 karakter hosszú jelszót, amely tartalmaz betűket és számokat is.
- 3. Érintse meg a "Done" gombot.



BEJELENTKEZÉS

- 1. Érintse meg a "Bejelentkezés meglévő fiókkal" gombot.
- 2. Adja meg a regisztrált fiók felhasználónevét és jelszavát.
- 3. Érintse meg a "Bejelentkezés" gombot.



Elfelejtett jelszó

Ha elfelejtette a jelszavát, vagy új jelszót szeretne beállítani, kövesse az alábbi lépéseket:

- 1. Érintse meg az "Forgot Password" gombot.
- 2. Adja meg a fiók felhasználónevét (e-mail címét), majd érintse meg az "Obtain verification code" gombot.

<

Enter verification

- 3. Adja meg az e-mailben kapott ellenőrző kódot.
- 4. Állítson be egy új jelszót, majd érintse meg a "Done" gombot.

			со	de				
Login	Forgot passw	ord	*	*	*	*	*	*
****** >	*****	>	Verificat	ion c	ode is	sent t	o you	r email
Email address	*******	x	******	****	Reser	nd(55s	;)	
Password			<					
Log in	Obtain verifica	tion code	Se	t P	ass	wo	rd	
Forgot password			**	**	**			٢
			6-20 charac	ters for p	assword,	includin	g characte	er, number
Login means that you agree with <u>User Agreement</u> and <u>Privacy Policy</u>					Do	ne		

HUN

AP MÓD

- 1. Kapcsolja be a beltéri egységet.
- 2. Kattintson a "+" jelre a kezdőképernyő jobb felső sarkában.
- 3. Válassza a "Large Home Appliances" lehetőséget.
- 4. Érintse meg a "Air conditioner (Wi-Fi)" logót.
- 5. Csatlakozzon a Wi-Fi hálózathoz.
- 6. Kövesse a képernyőn megjelenő utasításokat a Wi-Fi modul visszaállításához: - Az F sorozatú modem visszaállítása a "HEALTH" gomb 8-szori megnyomásával történik a távirányítón, 10 másodpercen belül.

 - A Q sorozatú modem visszaállítása a "[Cooling] és a [+] gombok egyidejű megnyomásával történik 3 másodpercig. Egy hangjelzés jelzi, hogy a modem sikeresen visszaállt. Jelölje be a "Confirm the device is reset" opciót, majd érintse meg a "Next" gombot.

- 7. A jobb felső sarokban változtassa meg a csatlakozási módot "AP mode"-ra, majd érintse meg a "Next" gombot.
- Adja meg a Wi-Fi jelszavát, amelyhez az okostelefonja csatlakozik, majd érintse meg a "Next" gombot.
- 9. Kövesse az utasításokat, és csatlakozzon az AC hotspotjához "SmartLifeXXXX".
- 10. Valós időben láthatja a csatlakozási folyamat százalékos arányát.

<	Add Manually Auto Scan	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical	Air Conditioning	Select 2.4 GHz Wi-Fi Network and enter password.	Reset the device first.	Reset the de EZ Mode Default
Sensors	Air Air Air Conditioner Conditioner (BLE+Wi-Fi) (Wi-Fi) (Zigbee)	If your Wi-Fi is 5GHz, please set it to be 2.4GHz. Common router setting method	Power on the device and confirm that the indicator is blinking rapidly. Note: please complete the network distribution within 3 minutes after resetting the device.	AP Mode the indicator is bit Note: please combinete the network distribution within 3 minutes after resetting the decen
Large Home Ap.,	Air Portable Air Air	R HIA BA		the demok.
Small Home Ap	(NB-loT) (Wi-Fi) (Wi-Fi) Refrigerator	→ 10-74 2.4034 × + ①		
Exercise &	888		Perform net pairing as prompted. >	Perform net pairing as prompted.
Security & Video Sur	Refrigerator Refrigerator Refrigerator (BLE+Wi-Fi) (Wi-Fi) (BLE) Water Heater	÷ =		
Gateway Control	Water Heater Water Heater Gas Water	Next		
Energy Entertainm	(BLE+Wi-Fi) (Wi-Fi) Heater (BLE+Wi-Fi)		Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking slowly.
ent Industry & Agriculture	Gas Water Solar water Heater beater heater (Wi-Fi) (BLE+Wi-Fi) (Wi-Fi)			
Cancel		Cancel	Cancel	Done
Conne	ect your mobile phone to	Address during		Added successfully
the de	vice's hotspot	Adding device Ensure that the device is powered on.	Adding device Ensure that the Wi-Fi signal is good.	Tesla AC 2 Device added successfully
⇒ si	maritilie XXXX 👻 🛈			
-	 Tuya Internet 			
2. Retun devices	n to this app and continue adding			
		01:57	01.36	
		Contraction of the second seco	Scan Register on Initialize the device.	

LÉGKONDICIONÁLÓ VEZÉRLÉSE

Az eszköz vezérlőképernyője automatikusan megjelenik az eszköz hozzáadása után. Az eszköz vezérlőképernyője manuálisan is megjeleníthető az eszköz nevére kattintva a kezdőképernyőn.

		٨		0	
		— Tes	a AC		
		Tes	la Air6		
		Tes	la Air3		
		(A)	Q: Ema	Q.	
÷	Tesla AC	Z		÷	Tesla AC
	Room temp: 200				Room temp: 200
	26				26
	♦ = 3 % 10				
paid.	Low UD Soing	Schedule		Hat	Auto UD Seing Sch
	Temp				Temp
Streep.	OFF	Q actor		Steep	OFF function

СПЕЦИФИКАЦИЈА НА WI-FI МОДУЛОТ И ИНСТРУКЦИИ ЗА РАБОТА

- Минимални спецификации за смарт телефон: Андроид верзија 5.0 или понова верзија iOS верзија 9.0 или понова верзија
- 2. Основни параметри за Wi-Fi модулот

Параметри	Детали
Фреквенција на мрежата	2.400 - 2.4835 GHz
WLAN стандарди	IEEE 802.11 b/g/n (канали 1-14, канали 1-13 за ЕУ/АВ, канали 1-11 за САД/ЦА)
Поддршка на протокол единица	IPv4/TCP/UDP/HTTPS/TLS/DNS
Безбедносна поддршка	WEP/WPA/WPA2/AES128
Поддршка за тип на мрежа	STA/AP/STA+AP
Макс. RF моќ	18.5 dbm
Bluetooth фреквенција	2.402 - 2.480 GHz
Bluetooth RF моќ	9 dbm

3. Прирачник за работа: Молиме користите едноставни инструкции подолу за референца.

Оперативни чекори	Оперативни елементи	Нова сметка	Повторно инсталирање на апликацијата (регистрирана порано)
Чекор 1	Преземање и инсталирање на апликацијата	Да прифаќам	Да прифаќам
Чекор 2	Активирање на апликацијата	Да прифаќам	Да прифаќам
Чекор 3	Регистрација на сметка	Да прифаќам	HE
Чекор 4	Приклучи се	Да прифаќам	Да прифаќам
Чекор 5	Додавање на контролен уред	Да прифаќам	Регистрираниот уред ќе остане

Забелешка: Ако сте регистрирале сметка и додале уред претходно, кога ќе ја реинсталирате апликацијата и ќе се пријавите, додадениот уред ќе остане.

ПРЕЗЕМАЊЕ И ИНСТАЛИРАЊЕ НА АПЛИКАЦИЈАТА

iOS







MKD

Tesla Smart

За Android смарт телефони

- **Метод 1:** Скенирајте го QR кодот со скенерот во пребарувачот, преземете и инсталирајте апликација.
- **Метод 2:** Отворете Google "Play Store" на вашиот паметен телефон и побарајте "Tesla Smart", преземете и инсталирајте апликација.

За IOS смарт телефони

- **Метод 1:** Скенирајте го QR кодот и ги следете инструкциите за да го отворите "AppStore", да ја преземете и инсталирате апликацијата.
- Метод 2: Отворете Apple "AppStore" на вашиот паметен телефон и побарајте "Tesla Smart Things", преземете и инсталирајте апликација.

Забелешка: Ве молиме овозможете дозволи за складирање/локација/камера за оваа апликација за време на инсталацијата. Во спротивно, може да се појават проблеми за време на работата.

РЕГИСТРАЦИЈА

- 1. Ако немате сметка, допрете на копчето "Регистрирај".
- 2. Прочитајте ја Политиката за приватност и допрете "Прифаќам".

Register Log in with Existing Account	regulations. When have fully read, unc all of the updated ⁴ Agreement. Please become familiar w and if you have any free to contactus.	you click[Agree, you derstood and accepted rivacy Policy and User takesome time to th ourprivacy policy, questions, please feel User Agreement
	Disagree	Agree

ПРИМЕНА

- 1. Допрете "Пријавите се со постоечка сметка".
- 2. Внесете корисничко име и лозинка за регистрираната сметка.
- 3. Допрете на копчето "Пријави".

		>
****	*****	х
Obt	ain verificati	on code
6		
I I.	Agree <u>User agreement</u> a	nd Privacy Policy

Country Ch	oosed
Search	
A	
Afghanistan	
Albania	
Algeria	
Angola	
Argentina	
Armenia	
Australia	z

РЕГИСТРАЦИЈА

- 1. Внесете го кодот за верификација што го добивте преку е-маил.
- 2. Поставете лозинка од 6-20 карактери, вклучувајќи букви и броеви.
- 3. Допрете "Готово".



ПРИМЕНА

- 1. Допрете "Пријавите се со постоечка сметка".
- 2. Внесете корисничко име и лозинка за регистрираната сметка.
- 3. Допрете на копчето "Пријави".



Заборавена лозинка

Ако сте ја заборавиле лозинката или сакате да ја ресетирате лозинката, следете ги следните чекори:

- 1. Допрете "Заборавена лозинка".
- 2. Внесете го вашето корисничко име (е-маил адреса) и го допрете копчето "Добиј код за верификација".

> X

cation code

- Внесете го кодот за верификација што го добивте преку е-маил.
- 4. Поставете нова лозинка и допрете на копчето "Готово".

Login	Forgot passwo
****** >	*****
Email address	******
Password	Obtain verificat
Log in	
Forgot password	
Login means that you agree with <u>User Agreement</u> and <u>Privacy Policy</u>	

←					
En	ter ve de	rifi	cati	ion	
*	* *	*	*	*	
Verificat	ion code is	sent t	o you	r email	
	, Keser	10(555	•)		
<					
Se	t Pass	wo	rd		
**	****	includio	z obaract	•	
0-20 charac	ers for password,	including	g charact	er, number	2
	Do	ne			

АР РЕЖИМ

- 1. Вклучете внатрешна единица.
- 2. Кликнете на "+" во горниот десен агол на почетниот екран.
- 3. Изберете "Големи домашни апарати".
- 4. Допрете на логото "Клима уред (Wi-Fi)".
- 5. Поврзете се со Wi-Fi мрежа.
- Следете ги инструкциите на екранот за да го ресетирате Wi-Fi модулот:

 За F серијата, ресетирањето се врши со притискање на копчето "HEALTH" 8 пати на далечинскиот управувач, во рок од 10 секунди.

- За Q серијата, ресетирањето се врши со притискање на копчињата "[Cool] и [+] истовремено за 3 секунди.

Звукот укажува на тоа дека модемот е успешно ресетиран. Отбележете "Потврди ресетирање на уредот" и допрете "Следни".

- 7. Во горниот десен агол, го сменете методот на поврзување во "АР режим" и допрете "Следни".
- Внесете лозинка за Wi-Fi мрежата на која е поврзан вашиот паметен телефон, а потоа докоснете "Напред".
- 9. Следете ги инструкциите и се поврзете со hot spot на климатизаторот "SmartLifeXXXX".
- 10. Можете да го следите процентот на напредок на конекцијата во реално време.

	Add Manually Auto So	an 🖯	Cancel	Cancel EZ Mode =	Cancel AP Mode =
Electrical Lighting Sensors	Air Conditioning	Air Conditioner (Zigbee)	Select 2.4 GHz Wi-Fi Network and enter password. If your W-Fi is 50Hz, please set it to be 2.40Hz, Common rooter setting method	Reset the device first. Power on the device and confirm that the indicator is takinging rapidly. Note please complete the network distributions within 3 minutes after resetting the device.	Reset the de EZ Mode Details Places power on the indicator of AP Mode Nota: places compared the network darticlution within 3 minutes after reserting the denice.
Large Home Ap Small Home Ap Kitchen Appliances Exercise & Health	Air Conditioner (NB-30T) Refrigerator Refrigerator Refrigerator	Air Conditioner (Wi-Fi)	+ 50 100 - 17	Perform net pairing as prompted. 3	Perform the pating do percepted
Security & Video Sur Gateway Control Energy Entertainm ent Industry & Agriculture	(ILL=YNFR) (IVF) Water Heater (ILL=YNFR) Gas Water Heater (ILL=YNFR) Gas Water Heater (ILL=YNFR)	(BLE)	₹ == A ⊕ Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking
Cancel			and a second		Deep
			Cancer	Cancel	Done
Connect the dev 1. Please of shown below 4 • Sm •	t your mobile phone rice's hotspot connect your phone to the hot will Mile and connection of the hot will Mile and connection of the hot manual for the hot will be manual for the hot will be hot will be manual for the hot will be hot will be hot will be manual for the hot will be hot will be hot will be hot will be hot will be manual for the hot will be hot wil	to spot	Adding device	Adding device Ensure that the Wi-Fi signal is good.	Added successfully Tests AC Device added successfully &
Connec the dev 1. Please c shown hele Sm # # # # # # # # # # # # # # # # # #	t your mobile phone to de's hotspot metalogies and the hot will be the top the second second second second the second second second second second the second second second second second top this app and continue ad	to spot	Adding device Desure that the device is powered on:	Lance Adding device Ensure that the Wi-Fi signal is good.	Added successfully Testa AC Device added successfully (2)

КОНТРОЛА НА КЛИМА УРЕД

Екранот за контрола на уредот автоматски ќе се појави откако уредот е додаден Екранот за контрола на уредот ќе се појави рачно со допирање на името на уредот на почетниот екран.

		۲		•	
		— Tes	ila AC		
		Tes	ila Air6		
		Tes	la Air3		
				0	
			₩. Eman	Q.	
		Z		÷	
	Room temp: 23°C				Room temp: 200
	♦ 5 5 8 10				9 9 1 9 8
Cold	Low DOSeting	Schedule		- 🔆 - Hat	Auto UD Swing Schedu
	Temp				Temp
C Steel	OFF	and low		Simp	OFF Puster

SPECIFICAȚII MODUL WI-FI ȘI INSTRUCȚIUNI DE FUNCȚIONARE

- 1. Specificații minime pe smartphone: Android 5.0 sau mai nou IOS 9.0 sau mai nou
- 2. Parametri de bază pentru modulul Wi-Fi

Parametri	Detalii
Frecvență rețea	2.400 - 2.4835 GHz
Standard WLAN	IEEE 802.11 b/g/n (canale 1-14,canale 1-13 for EU/AU,canale 1-11 for US/CA)
Protocol suport stack	IPv4/TCP/UDP/HTTPS/TLS/DNS
Suport securitate	WEP/WPA/WPA2/AES128
Suport tip rețea	STA/AP/STA+AP
Putere Max. RF	18.5 dbm
Frecvență Bluetooth	2.402 - 2.480 GHz
Putere Bluetooth RF	9 dbm

3. Instrucțiuni de funcționare. Instrucțiunile de mai jos sunt orientative.

Pași	Proces	Cont nou	Reinstalați aplicația (înregistrată anterior)
Pasul 1	Descărcați și instalați aplicația	DA	DA
Pasul 2	Activați aplicația	DA	DA
Pasul 3	Înregistrare cont	DA	NU
Pasul 4	Accesare cont	DA	DA
Pasul 5	Adăugați dispozitiv	DA	Dispozitivul înregistrat va rămâne.

Notă: Dacă ați înregistrat contul și dispozitivul anterior, când reinstalați aplicația și accesați contul din nou, dispozitivul adăugat va rămâne.

DESCĂRCAȚI ȘI INSTALAȚI APLICAȚIA







RO

Tesla Smart

Pentru Android

Metoda 1: Scanați codul QR cu un scaner de browser, descărcați și instalați aplicația.
 Metoda 2: Deschideți Google "Play Store" pe smartphone și căutați "Tesla Smart", descărcați și instalați aplicația.

Pentru IOS

Metoda 1: Scanați codul QR și urmați sfaturile pentru a intra în "AppStore", descărcați și instalați APP. Metoda 2: Deschideți Apple "AppStore" pe smartphone și căutați "Tesla Smart Things", descărcați și instalați APP.

Notă: Vă rugăm să activați permisiunile Stocare/Locație/Cameră pentru această aplicație în timpul instalării. În caz contrar, va avea unele probleme la funcționare.

ÎNREGISTRARE

- 1. Dacă nu aveți un cont, vă rugăm să apăsați butonul "Înregistrare".
- 2. Citiți Politica de confidențialitate și apăsați "De acord".



AUTENTIFICARE

- 1. Apăsați "Conectați-vă cu un cont existent".
- 2. Introduceți numele de utilizator și parola contului înregistrat.
- 3. Apăsați butonul "Conectați-vă".

*****	X
Obtain verificati	on code
I Agree User agreement a	nd <u>Privacy Policy</u>

Country Cho	oosed
Search	
А	
Afghanistan	
Albania	
Algeria	
Angola	
Argentina	
Armenia	
Australia	Y Z

ÎNREGISTRARE

- 1. Introduceți codul de verificare primit prin e-mail.
- 2. Setați parola cu 6-20 de caractere, inclusiv caractere și numere.
- 3. Apăsați "Terminat".



AUTENTIFICARE

- 1. Apăsați "Conectați-vă cu contul existent".
- 2. Introduceți numele de utilizator și parola contului înregistrat.
- 3. Apăsați butonul "Log in".



Ați uitat parola?

Dacă ați uitat parola sau doriți să o resetați, urmați acești pași:

- 1. Apăsați "Parola uitată".
- 2. Introduceți numele de utilizator al contului (adresa de e-mail) și apăsați butonul "Obține codul de verificare".

<

Enter verification

- 3. Introduceți codul de verificare primit prin e-mail.
- 4. Setați noua parolă și atingeți butonul "Terminat".

			co	de				
Login	Forgot passw	ord	*	*	*	*	*	*
******* >	*****	>	Manifiant					
Email address	********	X	*******	:****	Reser	nd(55s	o you ;)	remai
Password			<					
	Obtain verifica	tion code						
Log in			Se	t P	ass	wo	rd	
Forgot password			**	**	**			•
			6-20 charac	ters for p	assword,	includinj	g characte	er, numbe
Login means that you agree with <u>User Agreement</u> and					Do	ne		
Privacy Policy								

MOD AP

- 1. Porniți unitatea interioară
- 2. Faceți clic pe "+" în colțul din dreapta sus al ecranului de pornire.
- 3. Selectați "Electrocasnice mari"
- 4. Atingeți sigla "Aer condiționat (Wi-Fi)".
- 5. Conectați-vă la rețeaua Wi-Fi
- 6. Urmați comentariile de pe ecran pentru a reseta modulul Wi-Fi - Pentru modemul seria F se resetează apăsând butonul "SĂNĂTATE" de 8 ori de pe telecomandă, în decurs de 10 secunde - Pentru modemul din seria Q se resetează apăsând "[Răcire] și [+] simultan timp de 3 secunde Un semnal sonor va anunta că modemul a fost resetat cu succes
- 7. Verificați "Confirmați că dispozitivul este resetat" și atingeți "Următorul"
- 8. În colțul din dreapta sus, schimbați metoda de conectare la "Mod AP" și atingeți "Următorul"
- 9. Introduceți parola rețelei Wi-Fi la care este conectat smartphone-ul dvs., apoi atingeți "Next"
- 10. Urmați instrucțiunile și conectați-vă la hotspot-ul AC "SmartLifeXXXX"
- 11. Puteți vedea rata procentuală a procesului de conectare, în timp real.

<	Add Manually Auto Scan 🕀	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical Lighting	Air Conditioning	Select 2.4 GHz Wi-Fi Network and enter password. If your WFFI is 50Hz please set it to be 2 GHZ company reating antibod	Reset the device first. Power on the device and confirm that the indicator is blinking rapidly. Note: please complete the network	Reset the de EZ Mode Defaut Please power on the indicator is bi Note: please pombere une network
Sensors Large Home Ap	(BLE+Wi-Fi) (Wi-Fi) (Zigbre)	Look L. Common roads stating memory	distribution within 3 minutes after resetting the device.	distribution within 3 minutes after resetting the device.
Small Home Ap	Air Portable Air Air Conditioner Conditioner Conditioner (NB4oT) (Wi-Fi) (Wi-Fi)	x orth block		
Appliances Exercise & Health	Refrigerator Refrigerator Refrigerator	(î =	Perform net pairing as prompted, >	Perform net pairing as prompted
Security & Video Sur Gateway	Water Heater	۵ ۵		
Control	Water Heater Gas Water (BLE+W-Fi) (W-Fi) Heater (BLE+W-Fi)	Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking slowly.
Entertainm ent Industry &	Gas Water Solar water Heater heater (Wi-Fi) (Wi-Fi)			
Agnoutture				
Cancel		Cancel	Cancel	Done
Conne the der 1. Please shown be	ct your mobile phone to vice's hotspot connect your phone to the hotspot atow	Adding device Ensure that the device is powered on.	Adding device Ensure that the Wi-Fi signal is good.	Added successfully Tesla AC Device added successfully
✓ Sn	narsLife XXXX 👻 🗊			
2. Return devices	to this app and continue adding	Q		
		01:57	01:36	
		@C	00	

CONTROL APARAT AER CONDIȚIONAT

Ecranul de control al dispozitivului va apărea automat după adăugarea dispozitivului. Ecranul de control al dispozitivului va apărea manual atingând numele dispozitivului pe ecranul de pornire.

		۲		Đ		
		- Tesl	a AC			
		Tesl	a Air6			
		Tesl	a Air3			
		Â	¢	¢.		
		Norma	- Ema-	83%.		
÷	Tesla AC	×		÷		
÷	Tesla AC Room temp: 23°C	Z		÷	Tesla AC Room temp: 20°C	
÷	Tesla AC Room temp: 28°C 266°C	Z		¢	Tesla AC Room temp: 20°C 26°C	
÷	Tesla AC Room temp: 250 26°	Z		÷	Tasla AC Room temp: 200 2 6° x0	2
← cea	Tesla AC Room temp: 270 2 2 6 °C • C • C • C • C • C • C • C • C • C •	Z Senedule		€ Nor	Tesla AC Room temp: 300 2 6° 0 0° 0 0 00 AC	Z Scorduler
¢	Testa AC Room temp: 270 2 6 ° • • • • • • • • • • • • • • • • • • •	Z Somethe		¢	Tasla AC Room temp:::to: 2 6° Control Control Contr	L Scredute -
← End	Tesla AC Room temp: 250 2 2 6°C C C C C C C C C C C C C C C C C C C	Z Sometic Fundar		← Ker	Tesla AC Romitens: 200 2 6 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	Constant Nonestant Screenter

SPECIFIKACIJA WI-FI MODULA I UPUTSTVO ZA RAD

- 1. Minimalne specifikacije za pametan telefon: Android verzija 5.0 ili novija iOS verzija 9.0 ili novija
- 2. Osnovni parametri za Wi-Fi modul

Parametri	Detalji
Frekvencija mreže	2.400 - 2.4835 GHz
Standardi WLAN	IEEE 802.11 b/g/n (kanali 1-14, kanali 1-13 za EU/AU, kanali 1-11 za US/CA)
Podrška za protokolsku jedinicu	IPv4/TCP/UDP/HTTPS/TLS/DNS
Podrška za bezbednost	WEP/WPA/WPA2/AES128
Podrška za mrežni tip	STA/AP/STA+AP
Maks. RF snaga	18.5 dbm
Bluetooth frekvencija	2.402 - 2.480 GHz
Bluetooth RF snaga	9 dbm

3. Uputstvo za rad: Molimo koristite jednostavna uputstva u nastavku kao referencu.

Operativni koraci	Operativne stavke	Novi nalog	Ponovna instalacija aplikacije (registrovana ranije)
Korak 1	Preuzmite i instalirajte aplikaciju	DA	DA
Korak 2	Aktivirajte aplikaciju	DA	DA
Korak 3	Registracija naloga	DA	NE
Korak 4	Prijavite se	DA	DA
Korak 5	Dodajte uređaj za kontrolu	DA	Registrovani uređaj će ostati

Napomena: Ako ste registrovali nalog i dodali uređaj prethodno, kada ponovo instalirate aplikaciju i prijavite se, dodati uređaj će ostati.

PREUZMITE I INSTALIRAJTE APLIKACIJU







Tesla Smart

Za Android pametne telefone

Metod 1: Skrenirajte QR kod pomoću skenera u pretraživaču, preuzmite i instalirajte aplikaciju. Metod 2: Otvorite Google "Play Store" na svom pametnom telefonu i pretražite "Tesla Smart", preuzmite i instalirajte aplikaciju.

Za IOS pametne telefone

- Metod 1: Skrenirajte QR kod i pratite uputstva da biste otvorili "AppStore", preuzeli i instalirali aplikaciju.
- Metod 2: Otvorite Apple "AppStore" na svom pametnom telefonu i pretražite "Tesla Smart Things", preuzmite i instalirajte aplikaciju.

Napomena: Molimo vas da omogućite dozvole za Skladište/Lokaciju/Kameru za ovu aplikaciju tokom instalacije. U suprotnom, mogu nastati problemi tokom rada.

REGISTRACIJA

- 1. Ako nemate nalog, dodirnite dugme "Registruj se".
- 2. Pročitajte Politiku privatnosti i dodirnite "Prihvatam".

Register Log in with Existing Account	Notice We understandthe privacy. Inorder to our collection and information, we ha policy and user agr accordance with th regulations. When have fully read, und all of the updated Agreement. Please become familiar w and if you have any free to contactus. Privacy Policy and	importance of morefully present useof your personal werevised our privacy eementin detail in the latest laws and you click[Agree, you derstood and accepted Privacy Policy and User takesome time to ith ourprivacy policy, questions, please feel User Agreement
	Disagree	Agree

PRIJAVA

- 1. Dodirnite "Prijavite se sa postojećim nalogom".
- 2. Unesite korisničko ime i lozinku za registrovani nalog.
- 3. Dodirnite dugme "Prijavi se".

	>
*****	х
Obtain verifica	tion code
I Agree User agreement	t and Privacy Policy

Country Choosed		
Search		
A		
Afghanistan		
Albania		
Algeria		
Angola		
Argentina		
Armenia		
Australia	¥ Z	

REGISTRACIJA

- 1. Unesite verifikacioni kod koji ste primili putem e-pošte.
- 2. Postavite lozinku od 6-20 karaktera, uključujući slova i brojeve.
- 3. Dodirnite "Završeno".



PRIJAVA

- 1. Dodirnite "Prijavite se sa postojećim nalogom".
- 2. Unesite korisničko ime i lozinku za registrovani nalog.
- 3. Dodirnite dugme "Prijavi se".



Zaboravljena lozinka

Ako ste zaboravili lozinku ili želite da resetujete lozinku, pratite ove korake:

- 1. Dodirnite "Zaboravljena lozinka".
- 2. Unesite korisničko ime (e-mail adresu) i dodirnite dugme "Dobijte verifikacioni kod".

<

Enter verification

- 3. Unesite verifikacioni kod koji ste primili putem e-pošte.
- 4. Postavite novu lozinku i dodirnite dugme "Završeno".

		code
Login	Forgot password	* * * * * *
****** >	***** >	Verification code is sent to your email
Email address	******* X	**************************************
Password	Obtain verification code	<
Log in		Set Password
Forgot password		***** •
		6-20 characters for password, including character, number
Login means that you agree with <u>User Agreement</u> and <u>Privacy Policy</u>		Done

AP NAČIN

- 1. Uključite unutrašnju jedinicu.
- 2. Kliknite na "+" u gornjem desnom uglu početnog ekrana.
- 3. Izaberite "Veliki kućni aparati".
- 4. Dodirnite logo "Klima uređaj (Wi-Fi)".
- 5. Povežite se na Wi-Fi mrežu.
- 6. Pratite uputstva na ekranu da biste resetovali Wi-Fi modul:

- Za F seriju, resetovanje se vrši pritiskanjem dugmeta "HEALTH" 8 puta na daljinskom upravljaču, u roku od 10 sekundi.

- Za Q seriju, resetovanje se vrši pritiskanjem dugmadi "[Hlađenje] i [+] istovremeno na 3 sekunde. Zvuk signalizuje da je modem uspešno resetovan. Označite "Potvrdite da je uređaj resetovan" i dodirnite "Dalje".

- 7. U gornjem desnom uglu promenite metod povezivanja na "AP način" i dodirnite "Dalje".
- 8. Unesite lozinku za Wi-Fi mrežu na koju je vaš pametan telefon povezan, zatim dodirnite "Dalje".
- 9. Pratite uputstva i povežite se na hotspot klima uređaja "SmartLifeXXXX".
- 10. Možete pratiti procenat napretka povezivanja u realnom vremenu.

< .	Add Manually Auto Scan 🕀	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical Lighting Sensors	Air Conditioning	Select 2.4 GHz Wi-Fi Network and enter password. If your W-Fi is 5GHz, please set it to be 2.4GHz. Common route setting method	Reset the device first. Power on the device and confirm that the indicator is binking rapidly. Note: please complete the network distribution within a minutes after resetting the device.	Reset the de EZ Mode Defaut Please power on AP Mode the midicator is bit Note: please ordingers are network distribution within 2 minutes after resetting the denice
Large Home Ap Small Home Ap Kitchen Appliances Exercise & Health	A Conditioner Cond	**** *** * ## 1409 *** ***	Perform net pairing as prompted.	Perform het pairing as plangind
Security & Video Sur Gateway Control Energy Entertainm ent Industry & Agriculture	Water Heater Weber Hoster WELE-WWF9 GLE-WWF	A (b) Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking
Cancel		Cancel	Canaal	Done
Conne the der	ct your mobile phone to	Gaicer	Californ	
< Sn	vice's hotspot connect your phone to the hotspot low WILAN matriUfe XXXX T	Adding device Ensure that the device is powered on.	Adding device Ensure that the WiFi signal is good.	Added successfully
2. Return devices	Vice's hotspot competitioner to the hotspot form	Ading device Ensure that the slowest a powered on:	Adding device Ensure that the W-Fi signal is good.	Added successfully

48

KONTROLA KLIMA UREĐAJA

Ekran za kontrolu uređaja će se automatski pojaviti nakon dodavanja uređaja. Ekran za kontrolu uređaja će se pojaviti ručno dodirivanjem imena uređaja na početnom ekranu.



SPECIFIKACIJA MODULA WI-FI IN NAVODILA ZA DELOVANJE

- 1. Minimalne specifikacije pametnega telefona: Različica sistema Android 5.0 ali novejša Različica sistema IOS 9.0 ali novejša
- 2. Osnovni parametri za modul Wi-Fi

Parametri	Podrobnosti
Omrežna frekvenca	2.400 - 2.4835 GHz
Standardi WLAN	IEEE 802.11 b/g/n (kanali 1-14, kanali 1-13 za EU/AU, kanali 1-11 za ZDA/CA)
Podpora za sklad protokolov	IPv4/TCP/UDP/HTTPS/TLS/DNS
Varnostna podpora	WEP/WPA/WPA2/AES128
Podpora za tip omrežja	STA/AP/STA+AP
Največ. RF moč	18.5 dbm
Frekvenca modrega zoba	2.402 - 2.480 GHz
Moč modrega zoba RF	9 dbm

3. Navodila za uporabo. Kot referenco uporabite preprosta navodila v nadaljevanju.

Koraki delovanja	Operativni elementi	Nov račun	Ponovna namestitev programa APP (registriranega pred tem)
Korak 1	Prenesite in namestite aplikacijo	DA	DA
Korak 2	Aktivacija APP	DA	DA
Korak 3	Registracija računa	DA	NE
Korak 4	Prijava	DA	DA
Korak 5	Dodajanje naprave v nadzor	DA	Registrirana naprava bo ostala

Opomba: Če ste pred tem registrirali račun in dodali napravo, bo dodana naprava ostala, ko ponovno namestite aplikacijo APP in se prijavite.

PRENESITE IN NAMESTITE APLIKACIJO





iOS



Tesla Smart

Za pametne telefone Android

Način 1: Z optičnim bralnikom v brskalniku preberite kodo QR, prenesite in namestite aplikacijo APP.
 Način 2: Na pametnem telefonu odprite Google "Play Store" in poiščite "Tesla Smart", prenesite in namestite aplikacijo.

Za pametne telefone IOS

- **Način 1:** Prosimo, poskenirajte kodo QR in sledite nasvetom, da pridete v "AppStore", prenesite in namestite APP.
- Način 2: V pametnem telefonu odprite aplikacijo Apple "AppStore" in poiščite "Tesla Smart Things" ter prenesite in namestite aplikacijo.

Opomba: Med namestitvijo omogočite dovoljenja za shranjevanje/lokacijo/kamero za to aplikacijo APP. V nasprotnem primeru bo imela nekaj težav pri delovanju.

REGISTRACIJA

- 1. Če nimate računa, tapnite gumb "Registracija".
- 2. Preberite Pravilnik o zasebnosti in tapnite "Strinjam se".

Register Log in with Existing Account	Notice We understandthe privacy. Inorder to our collection and information, we ha policy and user agr accordance with th regulations. When have fully read, und all of the updated Agreement. Please become familiar w and if you have any free to contactus. Privacy Policy and	importance of morefully present useof your personal verevised our privacy eementin detail in e latest laws and you click[Agree, you ferstood and accepted rivacy Policy and User takesome time to th ourprivacy policy, questions, please feel
	Disagree	Agree

PRIJAVA

- 1. Tapnite "Prijavite se z obstoječim računom".
- 2. Vnesite uporabniško ime in geslo za registrirani račun.
- 3. Tapnite gumb "Prijavite se".



Country Choosed			
Search			
A			
Afghanistan			
Albania			
Algeria			
Angola			
Argentina			
Armenia			
Australia	1		

REGISTRACIJA

- 1. Vnesite kodo za preverjanje, ki ste jo prejeli po e-pošti.
- 2. Nastavite geslo s 6-20 znaki, vključno z znaki in številkami.
- 3. Tapnite "Končano".



PRIJAVA

- 1. Tapnite "Prijava z obstoječim računom".
- 2. Vnesite uporabniško ime in geslo za registrirani račun.
- 3. Tapnite gumb "Prijava".



Pozabljeno geslo

Če ste geslo pozabili ali ga želite ponastaviti, sledite naslednjim korakom:

- 1. Tapnite "Pozabljeno geslo".
- 2. Vnesite uporabniško ime računa (e-poštni naslov) in tapnite gumb "Pridobi kodo za preverjanje".

<

Enter verification

- 3. Vnesite kodo za preverjanje, ki ste jo prejeli po e-pošti.
- 4. Nastavite novo geslo in tapnite gumb "Done".

		code
Login	Forgot password	* * * * * *
****** >	***** >	Varification code is cont to your amail
Email address	***** X	*****************,Resend(55s)
Password	Obtain verification code	÷
Log in		Set Password
Forgot password		***** •
		6-20 characters for password, including character, number
Login means that you agree with <u>User Agreement</u> and <u>Privacy Policy</u>		Done

NAČIN AP

- 1. Vklop notranje enote
- 2. Kliknite "+" v zgornjem desnem kotu začetnega zaslona
- 3. Izberite "Veliki gospodinjski aparati".
- 4. Tapnite logotip "Klimatska naprava (Wi-Fi)".
- 5. Povezovanje z omrežjem Wi Fi
- 6. Za ponastavitev modula Wi-Fi sledite navodilom na zaslonu

- Modem serije F ponastavite tako, da v 10 sekundah 8-krat pritisnete gumb "ZDRAVJE" na daljinskem upravljalniku.

- Modem serije Q ponastavite tako, da za 3 sekunde hkrati pritisnete "[Cooling] in [+]. Zvočni signal bo sporočil, da je bil modem uspešno ponastavljen Preverite "Confirm the device is reset" in tapnite "Next".

- 7. V zgornjem desnem kotu spremenite način povezave v "AP mode" in tapnite "Next".
- 8. Vnesite geslo omrežja Wi-Fi, s katerim je povezan vaš pametni telefon, in tapnite "Naprej".
- 9. Sledite navodilom in se povežite z AC-točko "SmartLifeXXXX".
- 10. V realnem času si lahko ogledate odstotek procesa povezovanja.

<	Add Manually Auto	Scan 🕀	Cancel	Cancel EZ Mode =	Cancel AP Mode ==
Electrical	Air Conditionin	9	Select 2.4 GHz Wi-Fi	Reset the device first.	Reset the de
Lighting			Network and enter password.	Power on the device and confirm that the	Please power on AP Mode
Sensors	Air Air Conditioner Conditioner (BLE+Wi-Fi) (Wi-Fi)	Air Conditioner (Zigbee)	If your Wi-H is SGHz, please set it to be 2.4GHz. Common router setting method	Note: please complete the network distribution within 3 minutes after resetting the device.	Note: please complete the network distribution within 3 minutes after resetting the device.
Large Home Ap	Air Portable Air	Air	X 10.4: 10x		
Small Home Ap	Conditioner Conditioner (NB-IoT) (Wi-Fi)	Conditioner (Wi-Fi)	✓ WH-2.40hz + + ⊕		
Kitchen Appliances	Refrigerator				
Exercise & Health	Refrigerator Refrigerator (BLE+Wi-Fi) (Wi-Fi)	Refrigerator (BLE)		Perform net pairing as prompted. >	Perform net pairing as prompted.
Security & Video Sur	Water Heate		A		
Gateway Control					
Energy	(BLE+Wi-Fi) (Wi-Fi)	Heater (BLE+Wi-Fi)	Next	Confirm the indicator is blinking rapidly.	Confirm the indicator is blinking slowly.
Entertainm ent	Gas Water Solar water	Solar water			(
Industry &	Heater heater (Wi-Fi) (BLE+Wi-Fi)	(Wi-Fi)			
Agriculture					
Agricatore					
Cancel			Cancel	Cancel	Done
Cancel Conne the de	ct your mobile phon vice's hotspot	e to	Cancel Adding device	Cancel Adding device	Done Added successfully
Cancel Conne the de	ict your mobile phon vice's hotspot roonnect your phone to the h dow	e to Mapot	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Testa AC Descent address uncertaintie
Cancel Conne the de 1. Picase shown be	ct your mobile phon vice's hotspot connect your phone to the b drow	e to Mapat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Testa AC Dence added successfully
Cancel Conne the de 1. Please shown bu	ct your mobile phon vice's hotspot connect your phone to the b drow WELAN mart UTe XXXX	e to xispat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the WiFi signal is good.	Done Added successfully Tasla AC &
Cancel Connee the de 1. Please shown b	ct your mobile phon vice's hotspot roomed your phone to the h day wellow mariCle XXXX * Topo taxes	e to htspat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the WFI signal is good.	Done Added successfully Tesla AC Device added successfully
Cancel Conne the deal shown bine Shown bine	et your mobile phon vice's hotspot water of the set of the set water of the set mark (I-local) " the set of the set to the set of the set of the set to the set of the set of the set of the set the set of the s	e to stspat	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Cretia AC Device added successfully
Cancel Conne the de 1. Please shown bi	ct your mobile phon vice's hotspot annet your phone to she h fetor status marticli # XXX * Says taxes * Says taxes to this app and continue a	e to xtspot () deling	Cancel Adding device Ensure that the device is powered on.	Cancel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Certica AC Device added successfully
Cancel Connee the de 1. Piease shown h	ct your mobile phon vice's hotspot and the set of the set and the set of the set and the set of the set 's Gastaneed's to this app and continue a	e to Atsport	Cancel Adding device Ensure that the device a powered on.	Cancel Adding device Ensure that the W-Fi signal is good.	Done Added successfully Tests AC Protice added successfully
Cancel Conne 1. Please shown b Shown b 2. Return devices	ct your mobile phon vice's hotspot roumet your phone to the h down ward. To Stock mark. To Stock * Saa burks * Saa burks	e to stepor ()	Cancel Adding device Ensure that the device is powered on	Carcel Adding device Ensure that the Wi-Fi signal is good.	Done Added successfully Cerce added successfully Derice added successfully
Cancel Connection 1. Please shown in Source State 2. Return devices	ct your mobile phon vice's hotspot water of the second second second second water of the second second second second second second second second second second second second second seco	e to disport	Cancel Adding device Ensure that the device is powered on. In	Cancel Adding device Ensure that the Wi-Fi signal is good. 01.36	Done Added successfully Testa AC Device added successfully
Cancel Concee 1. Please shown in Concee 2. Return devices	ct your mobile phon vice's hotspot www.example.com www.example.com www.example.com results	e to stoor • ①	Cancel Adding device There that the device is powered on the dev	Cancel Adding device Ensure that the Wi-Fi signal is good. United States of Concentration of Concentra	Done Added successfully Tetia AC Device added successfully

UPRAVLJANJE KLIMATSKE NAPRAVE

Po dodajanju naprave se samodejno prikaže nadzorni zaslon naprave. Nadzorni zaslon naprave se prikaže ročno, tako da tapnete ime naprave na zaslonu Domov.





www.tesla.info